


# LINEA-4C

# LINEA-4C/W



Multi-frequency (433.92 MHz or 868 MHz) remote control with 4 button and duplicator function included.

# 1 - PRODUCT FEATURES

## 1.1 DESCRIZIONE

Multi-frequency (433.92 MHz or 868 MHz) remote control with 4-zone and duplicator function included. It's possible to duplicate remotes with single code or rolling code type 1, rolling code type 2 (brands BFT, V2 and FAAC) or make copies of already "cloned" remote controls, see paragraph No.3

## 1.2 TECHNICAL DATA

Power supply	Battery type CR2032
RF frequency	433.92MHz / 868 MHz
Channels	4
Dimensions	71x36x8 mm

# 2 - USE OF REMOTE CONTROL

The remote control can be used by programming it directly on compatible Nexta receivers or it can be used to duplicate existing transmitters.

## DIRECT PROGRAMMING ON COMPATIBLE RECEIVERS

The remote control can be associated with any Nexta Tech control unit, see the receiver control unit manual.

## COPY FUNCTION

The radio control has the function of duplication towards the transmitters present on the market with fixed code or rolling compatible type. See compatibility table in paragraph 4.

To duplicate a key of an existing transmitter:

1- carry out the procedure in paragraph 3 based on the original remote control "

2- insert the cloned key of the "copier remote control" in the receiver memory. The insertion can be done "manually" with access to the receiving unit or, if the transmitter allows it, with a procedure on the "copier radio control", see paragraph 4.

## CAUTION:




- Each button of the remote control can have a different function. Therefore it is possible to duplicate up to 4 remote controls using a single copier

### 3 - DUPLICATE REMOTES

#### Note



- If the RED LED flashes only 3 times and goes off, the code has not been learned correctly, then repeat the operation from point 1.
- Several radio transmitters codes can be duplicated and saved to each button
- Internal memory is rewritable.

#### 3.1 - PROCEDURE TO DUPLICATE REMOTES WITH SINGLE CODE OR ROLLING CODE TYPE 1



If the remote control is a fixed code


If the remote control is a rolling type 1



### 3.2 - PROCEDURE FOR THE DUPLICATION OF A TYPE 2 ROLLING CODE (BFT, V2, FAAC)


#### STEP 1

Press and hold button 1 of the “copier radio control”, and simultaneously press key 2 for 4 times



#### STEP 2


Release both buttons. At this point the RED LED of the “copier radio control” will emit a short Flash about every 2 sec.



#### STEP 3

Position the “remote control to be cloned” in front of the “copying radio control” at a distance of about 1-2 cm, then Press and hold the button to be copied of the “remote control to be cloned” and wait for the RED LED of the “copying radio control” to turn on steadily, then release the button.

The RED LED of the “copier remote control” will emit a short flash about every 2 sec.



If the remote control is a BFT model

If the remote control is a V2 model

If the remote control is a GENIUS model

#### STEP 4a

Now transmit the source code of the original BFT remote control (by pressing the button hidden on the back with a pin, or in the case of more recent models by simultaneously pressing buttons 1 and 2 until the LED of the original remote control lights up).

#### STEP 4b

Now transmit the source code of the original V2 remote control by pressing keys 1 and 2 simultaneously.

#### STEP 4c


Press keys 1 and 2 simultaneously and when the LED flashes release them (Note: THEY ARE THE KEYS OF THE DIAGONAL as shown in the image).



#### STEP 5

The RED LED of the “copier remote control” will now change flashing (faster flashing) and color (GREEN), confirming the correct learning of the code. This can take a few seconds.

this point, press the key of the “copier radio control” in which you want to store the code and keep it pressed until the LED turns off to confirm the correct learning of the code.




#### STEP 6

Add the “programmed copier radio control” with the remote learning procedure (depends on the model copied) or with a standard association procedure. See paragraph 4

### 3.3 - PROCEDURE FOR THE DUPLICATION OF A "COPIER REMOTE CONTROL" WITH ANOTHER COPIER REMOTE CONTROL

This procedure makes it possible to duplicate an already cloned button of a "copier radio control" on another "new copier radio control".



## 4 - LIST OF COMPATIBLE REMOTE CONTROLS AND METHOD OF INSERTION IN THE RECEIVER'S MEMORY

Below is the list of compatible rolling code remote controls and the method for inserting the "copying remote control" in the receiver based on the brand.

### TYPE A PROGRAMMING

Access the receiver, activate listening (see receiver manual) and then press the "copier radio control" button.

### TYPE B PROGRAMMING

Near the automation and before using the original remote control, press and hold down the "copying radio control" button until the LED starts flashing. Wait for the blinking to stop.

### TYPE C PROGRAMMING

Near the automation and before using the original remote control, press the "copier radio control" button 4/5 times.

BRAND MODEL	TYPE OF COPY
<b>ACM</b>	
TX2, TX2 COLOR, TX4	<b>A</b>
<b>ADYX</b>	
TE4433H BLUE, 433-HG BRAVO	<b>B</b>
<b>AERF</b>	
COMPACT, HY-DOM, MERCURI B, MERCURI C, SABUTON, MARS, SATURN, ST3/N, TERRA, TMP-1, TMP-2, UNITECH	<b>B</b>
<b>ALLMATIC</b>	
BROWN, BROWN RED, BRO.OVER, PASS, MINIPASS, TECH3, FOR4	<b>B</b>
<b>APERIO</b>	
GO, GO PRO, GO MINI	<b>A</b>
<b>APERTO (Sommer)</b>	
4020-TX03-434, TX02-434-2, TX02-868-2	<b>A</b>
<b>APRIMATIC</b>	
TR, TM4, TXM	<b>B</b>
<b>AVIDSEN</b>	
104251, 104250, 104250 OLD, 104250 RED, 104257, 104350, 654250, TX4 114253	<b>A</b>
<b>BALLAN</b>	
FM400, FM400E	<b>A</b>
<b>BENINCA</b>	
TO. GO. WV, TWV, ROLLKEY, APPLE, LOT WCV, CUPIDO, TO.GO. QV, HAPPY VA	<b>B</b>
IO, TO.GO. VA	<b>A</b>
<b>BFT</b>	
MITTO, MITTO M, MITTO RCB, MITTO A, TRC, GHIBLI, MURALE, KLEIO	<b>B</b>
<b>CARDIN</b>	
TRQ S449, TRQ S449 GREEN (PRECODE), TXQ S449, TXQ S449 GREEN, TRQ S486, TXQ S486, S437 TX, XRADO	<b>B</b>
<b>CASALI</b>	
GENIUS/CASALI A252RC	<b>B</b>

BRAND MODEL	TYPE OF COPY
<b>CHAMBERLAIN, LIFT MASTER, MOTOR LIFT</b>	
953ESTD, 371 LM, 971LM, 84330E, 94334CE, 94333E/94334E/94335E, 9747E, 1A5639-7, 1A5477, 1A6487, 132B2372, 94330EML/ 9333EML/94335EML, 84330EML/84333EML/84335EML, 8747EML	<b>A</b>
<b>CLEMSA</b>	
MUTANCODE, T, T-8, E-CODE N	<b>A</b>
MASTERCODE MV	<b>C</b>
<b>DASPI</b>	
ZERO RC	<b>A</b>
<b>DEA SYSTEM</b>	
PUNTO 278, GOLDR, GENIE R 273, GENIE R-GT2M, MIO TR, GT2M, TRN	<b>A</b>
<b>DITEC/ENTREMATIC</b>	
BIXLP, GOL4, BIXLG, ZEN	<b>B</b>
<b>DOORHAN</b>	
TRANSMITTER 4	<b>A</b>
<b>DOORMATIC</b>	
MILENY, MILENY-EVO	<b>A</b>
<b>ECOSTAR</b>	
RSC, RSE, RSZ	<b>A</b>
<b>ERREKA</b>	
IRIS, ROLLER 2, ROLLER 433, ROLLER 868, SOL433, SOL868, VEGA 433, VEGA 868	<b>B</b>
<b>FAAC</b>	
TML 433SLH, DL 868 SLH, XT 868 SLH, XT 433 SLH, T 868 SLH, T 433 SLH, XT 868 SLH BLACK, XT 433 SLH BLACK	<b>C</b>
<b>FADINI</b>	
JUBI-SMALL, JUBI 433, DIVO 71/4	<b>B</b>
<b>GENIUS</b>	
AMIGO JA332-JA334 868, AMIGOLD 868, KILO 433 JLC, KILO 868 JLC	<b>C</b>

BRAND MODEL	TYPE OF COPY
<b>GENIUS</b>	
BRAVO, ECHO	<b>B</b>
<b>GIBIDI</b>	
AU1600, AU1600 WOOD, AU1680, AU1680 WOOD, DOMINO, MAKO	<b>B</b>
<b>JCM</b>	
NEO, TWIN	<b>B</b>
<b>JCM</b>	
GO, GO PORTIS, GO NORTON, GO MINI	<b>A</b>
<b>KBLUE</b>	
ETH-TEL01	<b>A</b>
<b>KEY</b>	
900TXB-42R, TXB 44R, SUB 44R	<b>B</b>
<b>KING GATES</b>	
CLIPPER, STYLO	<b>B</b>
<b>KLING</b>	
KUA, KUA E, KUA S	<b>B</b>
<b>LABEL</b>	
SPYCO	<b>B</b>
<b>LIFE</b>	
FIDO	<b>A</b>
<b>MHOUSE</b>	
TX3, TX4, GTX4	<b>B</b>
<b>MOOVO</b>	
MT4G	<b>B</b>
<b>NICE</b>	
SMILO, FLOR-S, VERY-VR, FLOR-S ERA, ONE (ON), ON ERA, INTI, ERGO, PLANO, ONE (ON FM)	<b>B</b>
<b>NORMSTHAL</b>	
RCU 2/4 K, EA 433 2/4 K	<b>A</b>
<b>NORTON</b>	
NEO, TXCD	<b>B</b>
GO NORTON, GO MINI NORTON	<b>A</b>
<b>NOVOFERM</b>	
MCHS, MICRO-NOVOTRON 502, MINI-NOVOTRON 504, MICRO-NOVOTRON 502, MICRO-NOVOTRON 504, MICRO-NOVOTRON 31, MICRO-NOVOTRON 51, MINI-NOVOTRON 30, MININOVOTRON 50, MNHS, MINI NOVOTRON 522	<b>A</b>
<b>O&amp;O</b>	
TX, T.COM R4-2, T.COM R8-2, TWIN, TX (NEO)	<b>B</b>

BRAND MODEL	TYPE OF COPY
<b>PRASTEL</b>	
MTE, MPSTLE, MPSTP2E, TCE, BFOR, TRQ-P, SLIM-E	<b>B</b>
<b>PUJOL</b>	
TWIN, VARIO, VARIO MARS, VARIO OCEAN, NEO	<b>A</b>
<b>RIB</b>	
LITHIO	<b>A</b>
<b>ROPER</b>	
NEO	<b>B</b>
GO ROPER, GO MINI ROPER	<b>A</b>
<b>SABUTOM</b>	
BROOVER, BROSTAR	<b>B</b>
<b>SEAV</b>	
BE HAPPY RS, BE SMART	<b>A</b>
<b>SECULUX</b>	
NEO	<b>B</b>
<b>SILVELOX</b>	
Mhz 2007, QUARZ SAW	<b>A</b>
<b>SIMINOR</b>	
CVXNL, MITTO	<b>B</b>
SIM433	<b>A</b>
<b>SOMFY</b>	
K-EASY, K-EASY NEW, K-EASY OLD, MITTO, KEY GO RTS, TELIS RTS, KEYTIS RTS, KEYTIS RTS NS, ALARMA	<b>A</b>
<b>SOMMER</b>	
4010, 4011, 4014 TX03-434-2, 4013 TX03-434-4, 4020 TX03-868-4, 4026 TX03-868-2, 4022 TX02-434-2, 4025 TX02-868-2, 4031 TX08-868-4	<b>A</b>
<b>STAGNOLI</b>	
KALLISTO, VENUS AV223	<b>A</b>
<b>TAU</b>	
250K-SLIMRP, 250K-SLIMR, 250T-4RP	<b>B</b>
<b>TELCOMA</b>	
FM400E, FM400	<b>A</b>
<b>TOR LIFT</b>	
TORMIT4	<b>A</b>
<b>V2</b>	
TSC, TXC, TRC, HANDY, PHOENIX, PHOX 433, PHOENIX 868, PHOX 868	<b>B</b>
<b>VDS</b>	
ECO-R, TRQ P	<b>B</b>

CE



**LEF**  
*Lighting*

**LEF LIGHTING S.R.L.**

Via Rodolfo Morandi 9/11

50019 Sesto Fiorentino

Tel. 055.4217727

Firenze - ITALY

[www.leflighting.it](http://www.leflighting.it)

V1.0